



ISO 9001-2015 • C-DOT APPROVED • MIL STANDARD MIL-I-46058-C TYPE AR • ROHS COMPLIANCES

ELCLEAN PCB Assembly cleaning solvent to clean PCB after assembly. To remove the residual Flux, solder paste, ink, greasy surface, etc.

PCB assembly becomes clean and dry. Once the PCB assembly is clean the testing becomes easy without any current seepage, Arcing, and other relevant problems. After testing conformal coating can be applied for protection.

ELCLEAN can also be used to remove the pre-coated acrylic conformal coating. For this ELCLEAN is to be applied and gently brushed by an antistatic brush for servicing purposes.



Application

- Efficient solvent for cleaning and degreasing printed circuit board assemblies
- Removal of grime from electrical components
- · Cleaning contact points on wires and terminals
- Removal of contaminants and post-processing residues
- To be used while servicing PCB Assemblies
- Removal of Acrylic base-coated film for servicing purposes

Appearance: Clear, colourless liquid Odour: Hydrocarbon solvent Specific Gravity @ 25°C: 0.840 Pressure @ 25°C: 3.0 Bar Discharge rate: 1.3 g/sec

Solubility: Miscible with most organic solvents

Flash Point: 14°C

Packaging: 500 ml aerosol, 1 Litre, 5 Litre

Storage

The product may be stored at normal ambient temperatures and has a shelf life of not less than 24 months with correct storage. Aerosols should always be stored below 50°C, away from direct heat and naked flame.

MSDS

Health and Safety sheet available separately.



www.pcbconformalcoating.net

HO: 102, Ashwamedh Commercia Bldg. First Floor, Near Supreme HQ, Mumbai -Bangalore Highway,Baner, Pune, Maharashtra 411045.

Works: Sr No. 160/16A Vidya Valley School Road, Plot No.- 54,55 & 56, Mahadev Nagar, Sus Gaon, Dist-Pune- 411021.

Tel. : +91- 9545591323 , 9422003495, 9545494422 ,8421318400, Email : - coninspune@gmail.com

Refer MSDS prior to use

Disclaimer: MISREPRESENTATION ACT 1967 TRADE DESCRIPTIONS ACT 1968

The information given in this publication is based on our experience and reports from customers. There are many factors outside our control and knowledge which affect the use and performance of our products and for this reason, no warranty is given, express or implied. Users should make their own tests to determine the applicability of such information or the suitability of any products for their own particular purposes. Statements concerning the use of the products described herein are not to be construed as recommending the infringement of any patent and no liability for infringement arising out of any such use is to be assumed.